

Data sheet CPU 312SC (312-5BE13)

Technical data

Order no.	312-5BE13
Туре	CPU 312SC
General information	
Note	
Features	- SPEED7 technology
	16 x DI, 8 x DO 64 kB work memory Memory extension (max. 512 kB) PtP interface Also configurable via TIA-Portal
SPEED-Bus	-
Technical data power supply	
Power supply (rated value)	DC 24 V
Power supply (permitted range)	DC 20.428.8 V
Reverse polarity protection	1
Current consumption (no-load operation)	135 mA
Current consumption (rated value)	500 mA
Inrush current	11 A
l²t	0.7 A²s
Max. current drain at backplane bus	3 A
Power loss	8 W
Technical data digital inputs	
Number of inputs	16
Cable length, shielded	1000 m
Cable length, unshielded	600 m
Rated load voltage	DC 24 V
Reverse polarity protection of rated load voltage	1
Current consumption from load voltage L+ (without load)	70 mA
Rated value	DC 24 V
Input voltage for signal "0"	DC 05 V
Input voltage for signal "1"	DC 1528.8 V
Input voltage hysteresis	-
Frequency range	-
Input resistance	
Input current for signal "1"	6 mA
Connection of Two-Wire-BEROs possible	4
Max. permissible BERO quiescent current	1.5 mA
Input delay of "0" to "1"	0.1 / 0.35 ms
Input delay of "1" to "0"	0.1 / 0.35 ms
Number of simultaneously utilizable inputs horizontal configuration	16
Number of simultaneously utilizable inputs vertical configuration	16



Input characteristic curve	IEC 61131-2, type 1	A YASKAWA COMPANY
Initial data size	2 Byte	
Technical data digital outputs		
Number of outputs	8	
Cable length, shielded	1000 m	
Cable length, unshielded	600 m	
Rated load voltage	DC 24 V	
Reverse polarity protection of rated load voltage	-	
Current consumption from load voltage L+ (without load)	100 mA	
Total current per group, horizontal configuration, 40°C	3 A	
Total current per group, horizontal configuration, 60°C	2 A	
Total current per group, vertical configuration	2 A	
Output voltage signal "1" at min. current	L+ (-0.8 V)	
Output voltage signal "1" at max. current	L+ (-0.8 V)	
Output current at signal "1", rated value	0.5 A	
Output current, permitted range to 40°C	5 mA to 0.6 A	
Output current, permitted range to 60°C	5 mA to 0.6 A	
Output current at signal "0" max. (residual current)	0.5 mA	
Output delay of "0" to "1"	100 <i>µ</i> s	
Output delay of "1" to "0"	100 <i>µ</i> s	
Minimum load current	-	
Lamp load	5 W	
Parallel switching of outputs for redundant control of a load	possible	
Parallel switching of outputs for increased power	not possible	
Actuation of digital input	1	
Switching frequency with resistive load	max. 2.5 kHz	
Switching frequency with inductive load	max. 0.5 Hz	
Switching frequency on lamp load	max. 2.5 kHz	
Internal limitation of inductive shut-off voltage	L+ (-52 V)	
Short-circuit protection of output	yes, electronic	
Trigger level	1 A	
Number of operating cycle of relay outputs	-	
Switching capacity of contacts	-	
Output data size	1 Byte	
Technical data analog inputs		
Number of inputs	-	
Cable length, shielded	-	
Rated load voltage	-	
Reverse polarity protection of rated load voltage	-	
Current consumption from load voltage L+ (without load)	-	
Voltage inputs	-	
Min. input resistance (voltage range)	-	
Input voltage ranges	-	
Operational limit of voltage ranges		
Operational limit of voltage ranges with SFU		
Basic error limit voltage ranges	-	
Basic error limit voltage ranges with SFU	-	
U · · · U · · · · · · ·		



		A YASKAWA COMPANY
Destruction limit current	-	
Current inputs	-	
Max. input resistance (current range)	-	
Input current ranges	-	
Operational limit of current ranges	-	
Operational limit of current ranges with SFU	-	
Basic error limit current ranges	-	
Radical error limit current ranges with SFU	-	
Destruction limit current inputs (electrical current)	-	
Destruction limit current inputs (voltage)	-	
Resistance inputs	-	
Resistance ranges	-	
Operational limit of resistor ranges	-	
Operational limit of resistor ranges with SFU	-	
Basic error limit	-	
Basic error limit with SFU	-	
Destruction limit resistance inputs	-	
Resistance thermometer inputs	-	
Resistance thermometer ranges	-	
Operational limit of resistance thermometer ranges	-	
Operational limit of resistance thermometer ranges with SFU	-	
Basic error limit thermoresistor ranges	-	
Basic error limit thermoresistor ranges with SFU	-	
Destruction limit resistance thermometer inputs	-	
Thermocouple inputs	-	
Thermocouple ranges	-	
Operational limit of thermocouple ranges	-	
Operational limit of thermocouple ranges with SFU	-	
Basic error limit thermoelement ranges	-	
Basic error limit thermoelement ranges with SFU	-	
Destruction limit thermocouple inputs	-	
Programmable temperature compensation	-	
External temperature compensation	-	
Internal temperature compensation	-	
Technical unit of temperature measurement	-	
Resolution in bit	-	
Measurement principle	-	
Basic conversion time	-	
Noise suppression for frequency	-	
Initial data size		
Technical data analog outputs		
Number of outputs	-	
Cable length, shielded	-	
Rated load voltage	-	
Reverse polarity protection of rated load voltage	-	
Current consumption from load voltage L+ (without load)	-	
Voltage output short-circuit protection	-	
Voltage outputs	-	



Min. load resistance (voltage range)	_ A YASKAWA COMPAN
Max. capacitive load (current range)	
Max. inductive load (current range)	-
Output voltage ranges	-
Operational limit of voltage ranges	
Basic error limit voltage ranges with SFU	
Destruction limit against external applied voltage	
Current outputs	
Max. in load resistance (current range)	
Max. inductive load (current range)	-
Max. inductive load (current range)	-
Output current ranges	-
Operational limit of current ranges	-
Radical error limit current ranges with SFU	-
Destruction limit against external applied voltage	-
Settling time for ohmic load	-
Settling time for capacitive load	-
Settling time for inductive load	-
Resolution in bit	-
Conversion time	-
Substitute value can be applied	-
Output data size	-
Technical data counters	
Number of counters	2
Counter width	32 Bit
Maximum input frequency	10 kHz
Maximum count frequency	10 kHz
Mode incremental encoder	✓
Mode pulse / direction	✓
Mode pulse	✓
Mode frequency counter	✓
Mode period measurement	✓
Gate input available	✓
Latch input available	✓
Reset input available	-
Counter output available	✓
Load and working memory	
Load memory, integrated	512 KB
Load memory, maximum	512 KB
Work memory, integrated	64 KB
Work memory, maximal	512 KB
Memory divided in 50% program / 50% data	✓
Memory card slot	MMC-Card with max. 1 GB

Hardware configuration



		A YASKAWA COMPANY
Racks, max.	1	
Modules per rack, max.	8	
Number of integrated DP master	0	
Number of DP master via CP	4	
Operable function modules	8	
Operable communication modules PtP	8	
Operable communication modules LAN	8	
Status information, alarms, diagnostics		
Status display	yes	
Interrupts	yes	
Process alarm	yes	
Diagnostic interrupt	yes	
Diagnostic functions	no	
Diagnostics information read-out	possible	
Supply voltage display	green LED	
Group error display	red SF LED	
Channel error display	red LED per group	
Command processing times		
Bit instructions, min.	0.02 µs	
Word instruction, min.	0.02 µs	
Double integer arithmetic, min.	0.02 µs	
Floating-point arithmetic, min.	0.12 <i>µ</i> s	
Timers/Counters and their retentive characteri	stics	
Number of S7 counters	512	
Number of S7 times	512	
Data range and retentive characteristic		
Number of flags	8192 Byte	
Number of data blocks	4095	
Max. data blocks size	64 KB	
Max. local data size per execution level	510 Byte	
Blocks		
Number of OBs	15	
Number of FBs	2048	
Number of FCs	2048	
Maximum nesting depth per priority class	8	
Maximum nesting depth additional within an error OB	4	
Time		
Real-time clock buffered	1	
Clock buffered period (min.)	6 w	
Accuracy (max. deviation per day)	10 s	
Number of operating hours counter	8	
Clock synchronization	<b>√</b>	
Synchronization via MPI	Master/Slave	

<sup>©</sup> by VIPA GmbH, Ohmstr. 4, 91074 Herzogenaurach, Germany All data with reservation and subject to change. Publish date: 19.09.2014



Synchronization via Ethernet (NTP)

no

Input I/O address area1024 ByteOutput I/O address area1024 ByteInput process image maximal128 ByteOutput process image maximal128 ByteDigital inputs272Digital outputs264Digital outputs central272Digital outputs central264Integrated digital inputs16Integrated digital outputs8Analog inputs64Analog outputs, central64Analog outputs, central64Integrated analog outputs0Integrated analog outputs0Communication functionsIntegrated analog outputsPG/OP channelImage: CommunicationPG/OP channelImage: CommunicationS7 basic communication, user data per job76 Byte	
Input process image maximal128 ByteOutput process image maximal128 ByteDigital inputs272Digital outputs264Digital outputs central264Integrated digital inputs central264Integrated digital outputs16Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs64Integrated analog outputs0Integrated analog outputs0Communication functionsImage: CommunicationPG/OP channelImage: CommunicationS7 basic communication, user data per job76 Byte	
Output process image maximal128 ByteDigital inputs272Digital outputs264Digital outputs central272Digital outputs central264Integrated digital inputs16Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog outputs0Integrated analog outputs0Integrated analog outputs0Communication functionsImage: Central functionsPG/OP channelImage: Central function functionsPG/OP channelImage: Central function functio	
Digital inputs272Digital outputs264Digital inputs central272Digital outputs central264Integrated digital inputs16Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Integrated analog outputs0Size of GD packets, max.4Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Digital outputs264Digital inputs central272Digital outputs central264Integrated digital inputs16Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Integrated analog outputs0Communication functionsIntegrated analog outputsPG/OP channelImage: Central size of GD packets, max.Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Digital inputs central272Digital outputs central264Integrated digital inputs16Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Integrated analog outputs0Communication functionsIntegrated analog outputsPG/OP channelImage: CommunicationVisite of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Digital outputs central264Integrated digital inputs16Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Integrated analog outputs0Communication functions✓PG/OP channel✓Global data communication✓Number of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Integrated digital inputs16Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Integrated analog outputs0Communication functionsIntegrated analogPG/OP channelImage: CommunicationVisite of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Integrated digital outputs8Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Communication functions0PG/OP channelImage: Communication function functionsPG/OP channelImage: Communication function functionSize of GD packets, max.4Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Analog inputs64Analog outputs64Analog outputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Integrated analog outputs0Communication functionsVPG/OP channelVGlobal data communicationVNumber of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Analog outputs64Analog inputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Communication functions0PG/OP channelImage: Communication functionsPG/OP channelImage: Communication functionSize of GD packets, max.4Size of GD packets, max.22 ByteS7 basic communication, user data per job76 Byte	
Analog inputs, central64Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Communication functions0PG/OP channelImage: Communication function	
Analog outputs, central64Integrated analog inputs0Integrated analog outputs0Communication functions0PG/OP channelImage: Communication function functi	
Integrated analog inputs0Integrated analog outputs0Communication functionsPG/OP channelImage: CommunicationGlobal data communicationImage: CommunicationNumber of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communicationImage: CommunicationS7 basic communication, user data per job76 Byte	
Integrated analog outputs0Communication functionsPG/OP channelImage: CommunicationGlobal data communicationImage: CommunicationNumber of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communicationImage: CommunicationS7 basic communication, user data per job76 Byte	
Communication functionsPG/OP channelImage: Colspan="2">Image: Colspan="2"PG/OP channelImage: Colspan="2">Image: Colspan="2"Global data communicationImage: Colspan="2">Image: Colspan="2"Global data communicationImage: Colspan="2">Image: Colspan="2"Number of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communicationImage: Colspan="2"S7 basic communication, user data per job76 Byte	
PG/OP channelImage: Comparison of GD circuits, max.Size of GD packets, max.4Size of GD packets, max.22 ByteS7 basic communicationImage: Communication, user data per job76 Byte	
Global data communicationImage: CommunicationNumber of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communicationImage: CommunicationS7 basic communication, user data per job76 Byte	
Number of GD circuits, max.4Size of GD packets, max.22 ByteS7 basic communicationImage: Circuits of the second s	
Size of GD packets, max.22 ByteS7 basic communicationImage: Communication for the second s	
S7 basic communicationImage: CommunicationS7 basic communication, user data per job76 Byte	
S7 basic communication, user data per job 76 Byte	
S7 communication	
S7 communication as server	
S7 communication as client -	
S7 communication, user data per job 160 Byte	
Number of connections, max. 32	
PWM data	
PWM channels 2	
PWM time basis -	
Period length -	
Minimum pulse width -	
PtP communication -	
Functionality Sub-D interfaces	
Type X2	
Type of interface RS485	
Connector Sub-D, 9-pin,	
Electrically isolated -	female
MPI	female
MP²I (MPI/RS232) -	female
DP master -	female



DP slave Point-to-point interface

Turne	ХЗ
Type	
Type of interface	RS485
Connector Electrically isolated	Sub-D, 9-pin, female
	✓
MPI	-
MP²I (MPI/RS232)	-
DP master	-
DP slave	-
Point-to-point interface	1
Functionality MPI	
Number of connections, max.	32
PG/OP channel	1
Routing	-
Global data communication	<b>v</b>
S7 basic communication	
	✓
S7 communication	✓
S7 communication as server	✓
S7 communication as client	-
Transmission speed, min.	19.2 kbit/s
Transmission speed, max.	187.5 kbit/s
Functionality PROFIBUS master	
PG/OP channel	-
Routing	-
S7 basic communication	-
S7 communication	-
S7 communication as server	-
S7 communication as client	-
Activation/deactivation of DP slaves	-
Direct data exchange (slave-to-slave communication)	-
DPV1	-
Transmission speed, min.	-
Transmission speed, max.	-
Number of DP slaves, max.	-
Address range inputs, max.	-
Address range outputs, max.	-
User data inputs per slave, max.	-
User data outputs per slave, max.	-
Functionality PROFIBUS slave	
PG/OP channel	
Routing	
S7 communication	

\_

-



S7 communication as server	A YASKAWA COMPAN
S7 communication as client	·
Direct data exchange (slave-to-slave communication) DPV1	-
Transmission speed, min.	- -
Transmission speed, max.	- -
Automatic detection of transmission speed	
Transfer memory inputs, max.	-
Transfer memory outputs, max.	-
Address areas, max.	
User data per address area, max.	
Point-to-point communication	
PtP communication	
PIP communication	×
Interface isolated	<u>ح</u>
RS232 interface	-
RS422 interface	-
RS485 interface	A
Connector	Sub-D, 9-pin, female
Transmission speed, min.	150 bit/s
Transmission speed, max.	115.5 kbit/s
Cable length, max.	500 m
Point-to-point protocol	
ASCII protocol	1
STX/ETX protocol	1
3964(R) protocol	1
RK512 protocol	-
USS master protocol	1
Modbus master protocol	4
Modbus slave protocol	
Special protocols	-
Functionality RJ45 interfaces	Vr.
Type	X5
Type of interface	Ethernet 10/100 MBit
Connector Electrically isolated	RJ45
Electrically isolated	<b>v</b>
PG/OP channel	1
Number of connections, max.	4
Productive connections	•
Housing	
Material	PPE
Mounting	Rail System 300
Mechanical data	
Dimensions (WxHxD)	80 mm x 125 mm x 120 mm

© by VIPA GmbH, Ohmstr. 4, 91074 Herzogenaurach, Germany All data with reservation and subject to change. Publish date: 19.09.2014



Weight	410 g	A YASKAWA COMPANY
Environmental conditions		
Operating temperature	0 °C to 60 °C	
Storage temperature	-25 °C to 70 °C	
Certifications		
UL508 certification	yes	